



P-Connect connection gateway for safety devices



Description


The P-Connect connection gateway is a system that allows up to six (6) devices to be connected to a data network. Safety information is exchanged via PROFIsafe, CIP Safety™ or Safety over EtherCAT® extensions. Depending on its configurations, the gateway can transmit signals from two NG or NS series RFID safety switches with lock. The connection is performed safely using PROFIsafe, CIP Safety™ or Safety over EtherCAT® standards. Furthermore, the P-Connect gateway can be connected to a number of devices available in the Pizzato Elettrica catalogue. These include the BN series modular control device units, and AN series handles with integrated signalling LED.

Positioning in safe areas




The P-Connect connection gateway can be positioned in safe areas, away from the connected devices, to limit the risk of accidental damage or tampering.

Various configurations available



The P-Connect connection gateway is available in various configurations for every kind of application. Depending on the configuration in fact it comes with various types of connectors to connect the devices to be monitored.

Series connection



P-Connect connection gateways have two connectors. One supplies electrical power to the device and the other is used for the connection to the fieldbus network. This means several P-Connect gateways can be connected in series by simply connecting together the input and output connectors. This notably reduces the time required for installing, uninstalling and replacing components during maintenance.

Connection to PROFINET/PROFIsafe, EtherNet/IP™/CIP Safety™ and EtherCAT®/Safety over EtherCAT® networks



The gateway is capable of connecting multiple Pizzato safety devices to a single PROFINET/PROFIsafe, EtherNet/IP™/CIP Safety™ or EtherCAT®/Safety over EtherCAT® network. This ensures easy installation, even on very large machinery, and minimises wiring. Additionally, PROFIsafe, CIP Safety™ and Safety over EtherCAT® functionalities enable the gateway to be used to transmit signals to the PLC regarding safety functions for applications up to SIL3/PLC/Cat. 4.

Field diagnostics



BP A1PL....



BP A1CL....



BP A1EL....

The P-Connect connection gateway has integrated signalling LEDs to give the user a quick field diagnostic overview.

BP A1PLxxx, BP A1CLxxx:

- System status LED: multicolour signalling LED, which by lighting, flashing and using different colours, indicates the various device operating states, as well as any warnings or system errors;
- Network status LED: state monitoring of the connected Ethernet network;
- Module status LED: signalling of diagnostic events regarding communication protocols;
- L/A LEDs: two Link/Activity LEDs, corresponding to the two Ethernet ports on the device, signalling the status and connection speed.

BP A1ELxxx:

- "SYSTEM STATE": multicolour signal, which through sequences of lighting, flashing and colour changes, indicates the various operating states of the device to the user, as well as any warnings or errors concerning internal electronic components;
- "L/A EC IN/OUT": Two "Link/Activity" LEDs, corresponding to the two EtherCAT® ports on the device, signalling the status and connection speed;
- "RUN": indicates the status and operation of the EtherCAT® network;
- "ERROR": indicates EtherCAT® communication errors.

Diagnostic data



The P-Connect connection gateway allows quick access to diagnostic data such as internal temperature, gateway supply voltage, or current consumption of the connected devices. This makes it easy to monitor the gateway and the connected devices, quickly detecting any malfunctions.


Plug&Play device



With connectors on both the power side and the device side, the P-Connect connection gateway is a Plug&Play solution that saves installation time compared to traditional solutions that must be wired into a cabinet. What's more, it can quickly be replaced if there's a malfunction or if it gets damaged.



Selection diagram



Code structure

BP A1PL2001

Communication protocol	
P	PROFINET / PROFIsafe
C	EtherNet/IP™ / CIP Safety™
E	EtherCAT®/Safety over EtherCAT®

Power supply connector	
2	1 x M12 5-pole male connector + 1 x M12 5-pole female connector

Input configuration	
001	Configuration 001
002	Configuration 002
003	Configuration 003
004	Configuration 004
...	Other configurations on request

P-Connect connection gateway for safety devices



Main features

- Aluminium housing
- Protection degree IP65
- Operating temperature -15 °C ... +50 °C
- 5 LEDs integrated in the device for status indication
- Devices can be connected in series

Quality marks:



EC-type examination certificate: M6A 075157 0034
TÜV SÜD approval: Z10 075157 0033
UL approval: E530502
PROFINET approval: Z13641
PROFIsafe approval: Z20348
EtherCAT approval: 0x50495A_001

Features approved by TÜV SÜD

Operating voltage: 24 Vdc $\pm$ 15%
Operating temperature: -15°C ... +50°C
Pollution degree: 2
Overvoltage category: III

In compliance with standards: IEC 61508-1:2010 (SIL 3),
IEC 61508-2:2010 (SIL 3), IEC 61508-3:2010 (SIL 3),
EN ISO 13489-1:2015 (PL e, Cat 4),
EN IEC 62061:2021 (Maximum SIL 3), EN 61326-3-1:2017.

Please contact our technical department for the list of approved products.

Technical data

Aluminium housing, baked powder coating.
Protection degree:

IP65 acc. to EN 60529
with connectors of equal or higher protection degree

General data

Safety parameters	"Maximum SIL" up to	Performance Level (PL) up to	Cat. up to
Safety input monitoring function	3	e	4
Safety output activation function	3	e	4

Operating temperature: -15°C ... +50°C
Storage temperature: -30°C ... +70°C
Pollution degree: 2
Overvoltage category: III

Power supply electrical data

Rated voltage (U_e): 24 Vdc SELV/PELV
Supply voltage tolerance: $\pm$ 15%
Operating current at U_e voltage:
- no devices connected: 0.1 A
- maximum supported current: 3.1 A
Insulation voltage U_i : 32 V
Shock and vibration resistance: acc. to EN 60947-1
EMC protection: acc. to EN 61000-4 and EN 61326-3-1
External protection fuse: 4A type gG for a single BP gateway; for series connection the total load must be calculated.

Input and output circuits

Number of safety inputs: 3 dual-channel
Number of safety outputs: 1 dual channel (or 2 single channel)
Number of non-safety inputs: 14
Number of non-safety outputs: 24
Number of test outputs: 2
Maximum voltage at non-safety inputs: 24 Vdc
Voltage at non-safety outputs: 24 Vdc
Maximum control current at non-safety outputs: 50 mA
Maximum current at test outputs: 100 mA
Maximum current at safe outputs: 250 mA

In compliance with standards:

EN 60947-1, EN 61326-1, EN 61326-3-1, UL 508, CSA C22.2 No. 14, EN IEC 63000, EN 60529, IEC 61784-3-3, EN 61508, EN IEC 62061, EN ISO 13849-1, EN 61131-2.

Compliance with the requirements of:

Machinery Directive 2006/42/EC, EMC Directive 2014/30/EU, RoHS Directive 2011/65/EU.



Setting/changing IP addresses

PROFINET/PROFIsafe networks


The PROFIsafe F - Address identifies the device on the PROFIsafe network with a unique ID, protecting standard address mechanisms such as IP addresses. The safety address (F - Address) must be set using the 8 DIP switches located under the cover of the P-Connect gateway, labelled "ADDRESS". This value can be set from 1 to 255 and must be unique for every device connected to the network. Restart the device after setting the F - Address. Switches SW1 and SW2 are not used in this application.

EtherNet/IP™/CIP Safety™ networks

The housing contains 8 "ADDRESS" DIP switches that can be modified by the user and enable selection of one of the following modes:

- IP can be freely modified using Logix Designer (if all DIP switches are set to ON);
- IP fixed and set via hardware.

These 8 DIP switches represent the binary equivalent of the last octet of the IP address. The remainder (the first 3 groups of eight) is fixed to 192.168.1.xxx. You can therefore set a value between 1 and 254 (255 activates the change via software) taking care that the address is not already in use by other devices on the network. Restart the device after setting the F - Address. Switches SW1 and SW2 are not used in this application.



EtherCAT®/Safety over EtherCAT® networks


The safe address (FSOE Address) provides a unique identification of the device on the EtherCAT® network. The safe FSOE Address in TwinCAT 3 is set in the Safety logic tab and it must correspond to the physical address set by means of two DIP switches within the BP housing. The FSOE Address can be set from 1 to 255 and must be unique for each network device (The factory default address is set to 1). After setting the safe address, the device must be restarted. Switches SW1 and SW2 are not used in this application.

Emergency stop buttons



Some of the P-Connect gateway configurations can be used to manage up to two series of emergency stop buttons connected internally in series to the gateway. If you are not going to use both series of emergency stop buttons, bypass one of them using the "DIP3" switch (called "E-STOP BYPASS") located under the cover of the P-Connect gateway. If switches "1" and "2" are set to the "ON" position, the first series of connected emergency stop buttons is bypassed; while switches "4" and "5" activate the bypass for the second series of connected emergency stop buttons. The switches must only be switched when the P-Connect gateway is OFF, to prevent incoherent input test signal readings.


Dimensional drawings




All values in the drawings are in mm

BP A1•L2001

Solution with NG series switches, P-KUBE Krome safety handle and BN series control device units



Solution with NS series switches, P-KUBE Krome safety handle and BN series control device units



Note: the position of the connectors in the diagram is for illustrative purposes only.



Selection table for BP A1•L2001 devices

	Description	Quantity	Article number	
	RFID safety switch with lock, with separate actuator, NG/NS/NX series	2	NG ••••311A-F3•K958 ⁽¹⁾ NG ••••321A-F3•K958 ⁽¹⁾ NG ••••411A-F3•K958 ⁽¹⁾ NG ••••421A-F3•K958 ⁽¹⁾ NS •3••••P•-F4• ⁽¹⁾ NX •3•••1•P•-F6• ⁽¹⁾	NG ••••311B-F3•K958 ⁽¹⁾ NG ••••321B-F3•K958 ⁽¹⁾ NG ••••411B-F3•K958 ⁽¹⁾ NG ••••421B-F3•K958 ⁽¹⁾ NS •4••••P•-F4• ⁽¹⁾ NX •4•••1•P•-F6• ⁽¹⁾
	P-Connect connection box	1	BP A1•L2001	BP A1•L2001
	P-KUBE Krome safety handle with illuminated white grip with control device	2	AN G1B00••-PM• ^{(1) (2)}	AN S1B00••-PM• ^{(1) (2)}
	Signalling device chosen by installer, to be used as an alternative to the P-KUBE Krome safety handle (for example: indicator light tower)	1	Check that the electrical connections of the chosen device are compatible with the diagrams shown in the paragraph "Pin assignments of usable devices"	
	BN series control device unit with 3 control devices	2	BN AC3Z••• ^{(1) (3)}	BN AC3Z••• ^{(1) (3)}

Notes:

⁽¹⁾ for the configurations, refer to pages 169, 187, 205, 251 and 305 of the General Catalogue Safety Devices 2025-2026, or contact technical assistance.

⁽²⁾ Only configurations with M12 8-pole connector.

⁽³⁾ Only configurations with two non-illuminated devices with 1NO or 1NC, an emergency stop button 2NC, with M12 8-pole connector.

⚠ Attention: The articles listed above correspond to the maximum configuration that can be realised with the P-Connect connection gateway. Solutions with fewer devices can be implemented. If devices with emergency stop buttons are removed, the internal dip switches must be set accordingly to correctly configure the internal electronics of the connection system.

Compatible connectors with cable

Article	Description
VF CF5•••M	M12 male connector with cable, 5-pole
VF CA5•••M	M12 female connector with cable, 5-pole
VF CA5•••M-MD	M12 extension cable, 5-pole
VF CA8•••M-MD	M12 extension cable, 8-pole

Note: For the article codes of available connectors with cable refer to the chapter "Accessories".


Connections

Article	Power supply ports	Network ports	Device inputs					
BP A1•L2001								
	1 x M12, 5-pole, male 1 x M12, 5-pole, female	2 x M12, 4-pole, female, D-coded	M12, 8-pole, female	M12, 8-pole, female	M12, 8-pole, female	M12, 8-pole, female	M12, 8-pole, female	M12, 8-pole, female

Note: For the internal connections of usable devices, refer to pages 13-16.

BP A1•L2002



Solutions with NG/NS series switch, P-KUBE Krome safety handle, BN series control device unit, signalling device, safety device with OSSD safety outputs and control device unit including emergency stop



Note: the position of the connectors in the diagram is for illustrative purposes only.



Selection table for BP A1•L2002 devices

	Description	Quantity	Article number	
	RFID safety switch with lock, with separate actuator, NG/NS/NX series	1	NG ••••311A-F3•K958 ⁽¹⁾ NG ••••321A-F3•K958 ⁽¹⁾ NG ••••411A-F3•K958 ⁽¹⁾ NG ••••421A-F3•K958 ⁽¹⁾ NS •3••••P•-F4• ⁽¹⁾ NX •3•••1•P•-F6• ⁽¹⁾	NG ••••311B-F3•K958 ⁽¹⁾ NG ••••321B-F3•K958 ⁽¹⁾ NG ••••411B-F3•K958 ⁽¹⁾ NG ••••421B-F3•K958 ⁽¹⁾ NS •4••••P•-F4• ⁽¹⁾ NX •4•••1•P•-F6• ⁽¹⁾
	Safety device with OSSD safety outputs, at the user's discretion	1	Check that the electrical connections of the chosen device are compatible with the diagrams shown in the paragraph "Pin assignments of usable devices"	
	P-Connect connection box	1	BP A1•L2002	
	BN series control device unit with 4 control devices	1	BN AC4Z••• ^{(1) (2)}	
	Signalling device chosen by the user (for example: indicator light tower)	1	Check that the electrical connections of the chosen device are compatible with the diagrams shown in the paragraph "Pin assignments of usable devices"	
	P-KUBE Krome safety handle with illuminated white grip with control device	1	AN G1B00••-PM• ^{(1) (3)} AN S1B00••-PM• ^{(1) (3)}	
	Control device unit including emergency stop and luminous disc for signalling	1	ES AC31••• ^{(1) (3)} ES AC31687 (Mushroom with rotary release and 2NC) ES AC31688 (Mushroom with push-pull release and 2NC) ES AC31689 (Mushroom with rotary release, 1NC self-monitored and 1NC standard) ES AC31690 (Mushroom with push-pull release, 1NC self-monitored and 1NC standard) BN AC1ZA06 (Mushroom with rotary release and 2NC)	

Notes:

⁽¹⁾ for the configurations, refer to pages 169, 187, 205, 251, 295 and 305 of the General Catalogue Safety Devices 2025-2026, or contact technical assistance.

⁽²⁾ Only configurations with four buttons 1NO + LED, M12 12-pole connector.

⁽³⁾ Only configurations with M12 8-pole connector.

For further configurations, please contact technical assistance.

⚠ Attention: The articles listed above correspond to the maximum configuration that can be realised with the P-Connect connection gateway. Solutions with fewer devices can be implemented. If devices with emergency stop buttons are removed, the internal dip switches must be set accordingly to correctly configure the internal electronics of the connection system.

Compatible connectors with cable

Article	Description
VF CF5•••M	M12 male connector with cable, 5-pole
VF CA5•••M	M12 female connector with cable, 5-pole
VF CA5•••M-MD	M12 extension cable, 5-pole
VF CA8•••M-MD	M12 extension cable, 8-pole
VF CA12•••M-MD	M12 extension cable, 12-pole

Note: For the article codes of available connectors with cable refer to the chapter "Accessories".


Connections

Article	Power supply ports	Network ports	Device inputs					
BP A1•L2002								
	1 x M12, 5-pole, male 1 x M12, 5-pole, female	2 x M12, 4-pole, female, D-coded	M12, 8-pole, female	M12, 5-pole, female	M12, 12-pole, female	M12, 8-pole, female	M12, 8-pole, female	M12, 8-pole, female

Note: For the internal connections of usable devices, refer to pages 13-16.

BP A1•L2003

Solution with NG/NS series switches and P-KUBE Krome safety handles



Note: the position of the connectors in the diagram is for illustrative purposes only.



Selection table for BP A1•L2003 devices

	Description	Quantity	Article number	
	RFID safety switch with lock, with integrated control devices, with separate actuator, NG/NS/NX series	2	NG •••311C-F3•K60• ⁽¹⁾ NG •••321C-F3•K60• ⁽¹⁾ NG •••411C-F3•K60• ⁽¹⁾ NG •••421C-F3•K60• ⁽¹⁾ NG •••311D-F3•K60• ⁽¹⁾ NG •••321D-F3•K60• ⁽¹⁾ NG •••411D-F3•K60• ⁽¹⁾ NG •••421D-F3•K60• ⁽¹⁾ NS •3••STK-F4•N•• ⁽¹⁾	NG •••312V-F3•K60• ⁽¹⁾ NG •••322V-F3•K60• ⁽¹⁾ NG •••412V-F3•K60• ⁽¹⁾ NG •••422V-F3•K60• ⁽¹⁾ NG •••315R-F3•K60• ⁽¹⁾ NG •••325R-F3•K60• ⁽¹⁾ NG •••415R-F3•K60• ⁽¹⁾ NG •••425R-F3•K60• ⁽¹⁾ NS •4••STK-F4•N•• ⁽¹⁾
	P-Connect connection box	1	BP A1•L2003	
	P-KUBE Krome safety handle with illuminated white grip with control device	2	AN G1B00••-PM• ^{(1) (2)} AN S1B00••-PM• ^{(1) (2)}	

Notes:

⁽¹⁾ only codes with with 19-pole M23 connector. For the configurations, refer to pages 169, 187, 205 and 251 of the General Catalogue Safety Devices 2025-2026, or contact technical assistance.

⁽²⁾ Only configurations with M12 8-pole connector.

⚠ Attention: The articles listed above correspond to the maximum configuration that can be realised with the P-Connect connection gateway. Solutions with fewer devices can be implemented. If devices with emergency stop buttons are removed, the internal dip switches must be set accordingly to correctly configure the internal electronics of the connection system.

Compatible connectors with cable

Article	Description
VF CF5•••M	M12 male connector with cable, 5-pole
VF CA5•••M	M12 female connector with cable, 5-pole
VF CA5•••M-MD	M12 extension cable, 5-pole
VF CA8•••M-MD	M12 extension cable, 8-pole
VF CA19•••S-SD	M23 extension cable, 19-pole

Note: For the article codes of available connectors with cable refer to the chapter "Accessories".


Connections

Article	Power supply ports	Network ports	Device inputs			
BP A1•L2003	 1 x M12, 5-pole, male 1 x M12, 5-pole, female	 2 x M12, 4-pole, female, D-coded	 1 M23, 19-pole, female	 2 M23, 19-pole, female	 3 M12, 8-pole, female	 4 M12, 8-pole, female


Note: For the internal connections of usable devices, refer to pages 13-16.

BP A1•L2004

Solution with NG/NS/NX/ST series switches (series connection with Y-shaped connectors) and BN series control device units



Solution with up to 6 NG/NS/NX/ST series switches (series connection with Y-shaped connectors)





Note 1: the position of the connectors in the diagram is for illustrative purposes only.

Note 2: the unlocking command can independently control the two series of interlocks, but not a single device.



Selection table for BP A1•L2004 devices

	Description	Quantity	Article number	
	RFID safety switch with lock, with integrated control devices, with separate actuator, NG/NS/NX series. ST series RFID safety sensors	Up to 6	NG •••311A-F3•K95• ⁽¹⁾ NG •••321A-F3•K95• ⁽¹⁾ NG •••411A-F3•K95• ⁽¹⁾ NG •••421A-F3•K95• ⁽¹⁾ NG •••311B-F3•K95• ⁽¹⁾ NG •••321B-F3•K95• ⁽¹⁾ NG •••411B-F3•K95• ⁽¹⁾ NG •••421B-F3•K95• ⁽¹⁾ NS •3•••Q•-F4•N••• ⁽¹⁾ NX •3•••1•Q•-F6• ⁽¹⁾ ST ••3••M• ⁽¹⁾ ST ••4••M• ⁽¹⁾ ST ••5••M• ⁽¹⁾	NG •••311A-F3•K960 ⁽¹⁾ NG •••321A-F3•K960 ⁽¹⁾ NG •••411A-F3•K960 ⁽¹⁾ NG •••421A-F3•K960 ⁽¹⁾ NG •••311B-F3•K960 ⁽¹⁾ NG •••321B-F3•K960 ⁽¹⁾ NG •••411B-F3•K960 ⁽¹⁾ NG •••421B-F3•K960 ⁽¹⁾ NS •4•••Q•-F4•N••• ⁽¹⁾ NX •4•••1•Q•-F6• ⁽¹⁾ ST ••7••M• ⁽¹⁾ ST ••8••M• ⁽¹⁾ ST ••9••M• ⁽¹⁾
	P-Connect connection box	1	BP A1•L2004	
	BN series control device unit with 3 or 4 control devices (2 or 3 illuminated buttons and one emergency stop button)	Up to 4	BN AC3Z••• ⁽¹⁾⁽²⁾ BN AC4Z••• ⁽¹⁾⁽²⁾	

Notes:

⁽¹⁾ For the configurations, refer to pages 51, 169, 187, 205 and 305 of the General Catalogue Safety 2025-2026, or contact technical assistance.

⁽²⁾ Only configurations with M12 12-pole connector, 2 or 3 illuminated buttons and emergency stop button.


⚠ Attention: The articles listed above correspond to the maximum configuration that can be realised with the P-Connect connection gateway. Solutions with fewer devices can be implemented. If devices with emergency stop buttons are removed, the internal dip switches must be set accordingly to correctly configure the internal electronics of the connection system.

Compatible connectors with cable

Article	Description
VF CF5•••M	M12 male connector with cable, 5-pole
VF CA5•••M	M12 female connector with cable, 5-pole
VF CA5•••M-MD	M12 extension cable, 5-pole
VF CA12•••M-MD	M12 extension cable, 12-pole
VF CY201P0	M12 connector, Y-shaped, for series connections
VF CY100P0	M12 terminating plugs for series connections, 4-pole

Note: For the article codes of available connectors with cable refer to the chapter "Accessories".

Connections

Article	Power supply ports	Network ports	Device inputs					
BP A1•L2004	 1 x M12, 5-pole, male 1 x M12, 5-pole, female	 2 x M12, 4-pole, female, D-coded	 M12, 5-pole, female	 M12, 5-pole, female	 M12, 12-pole, female	 M12, 12-pole, female	 M12, 12-pole, female	 M12, 12-pole, female

Note: For the internal connections of usable devices, refer to pages 13-16.

Pin assignments of usable devices

DATA connectors

ETH 1
M12, 4-pole, female, D-coded




ETH 2
M12, 4-pole, female, D-coded



Pin	Function	Pin	Function
1	TX +	1	TX +
2	RX +	2	RX +
3	TX -	3	TX -
4	RX -	4	RX -


POWER SUPPLY connectors

POWER IN
M12, 5-pole, male, A-coded



Pin	Function
1	+24 Vdc
2	0 Vdc
3	0 Vdc
4	+24 Vdc
5	GND


POWER OUT
M12, 5-pole, female, A-coded



Pin	Function
1	+24 Vdc
2	0 Vdc
3	0 Vdc
4	+24 Vdc
5	GND


BP A1•L2001

Connectors no. 1 & 2: NG - NS series safety switches




Pin	Type	P-Connect side	NG - NS side
1	O	+24 Vdc power supply	A1
2	I	Actuator enabled signal input	O3
3	O	0 Vdc power supply	A2
4	I	Safety input IS1/IS3	OS1
5	O	Solenoid activation command OS1	IE2
6	O	Actuator programming / reset	I3
7	I	Safety input IS2/IS4	OS2
8	O	Solenoid activation command OS2	IE1

Connectors no. 3 & 4: BN AC3•••• series control device units



Pin	Type	P-Connect side	BN side
1	O	+24 Vdc power supply	Power supply +24 V
2	I	Non-safety input for contact of button 1	Button 1 contact
3	-	Disconnected	Disconnected
4	I	Non-safety input for contact of button 2	Button 2 contact
5	O	Test output TO1	Emergency stop button test input
6	I	Safety input for emergency stop button NC contact	Emergency stop button NC safety contact
7	O	Test output TO2	Emergency stop button test input
8	I	Safety input for emergency stop button NC contact	Emergency stop button NC safety contact

Connectors no. 5 & 6: AN series safety handles




Pin	Type	P-Connect side	AN side
1	I	0 Vdc power supply	Power supply 0 V
2	O	+24 Vdc power supply	Power supply +24 V
3	O	Control output LED 1	Control input green LED (G)
4	O	Control output LED 4	Button LED control input
5	O	+24 V output for button contact	Button NO voltage-free contact input
6	I	Input for button contact	Button NO voltage-free contact output
7	O	Control output LED 2	Control input blue LED (B)
8	O	Control output LED 3	Control input red LED (R)




BP A1•L2002

Connector no. 1: NG - NS series safety switches




Pin	Type	P-Connect side	NG - NS side
1	O	+24 Vdc power supply	A1
2	I	Actuator enabled signal input	O3
3	O	0 Vdc power supply	A2
4	I	Safety input IS1	OS1
5	O	Solenoid activation command OS1	IE2
6	O	Actuator programming / reset	I3
7	I	Safety input IS2	OS2
8	O	Solenoid activation command OS2	IE1

Connector no. 2: ST series safety sensors




Pin	Type	P-Connect side	ST side
1	O	+24 Vdc power supply	A1
2	I	Safety input IS3	OS1
3	O	0 Vdc power supply	A2
4	I	Safety input IS4	OS2
5	I	Signalling input	O3

Connector no. 3: BN AC4••• series control device units




Pin	Type	P-Connect side	BN side
1	O	+24 Vdc power supply	+24 Vdc power supply
2	O	Position 1 LED control output	Position 1 LED control input
3	I	0 Vdc power supply	0 Vdc power supply
4	I	Input for button 1 contact	Button 1 contact
5	I	Input for button 2 contact	Button 2 contact
6	O	Position 2 LED control output	Position 2 LED control input
7	I	Input for button 3 contact	Button 3 contact
8	O	Position 3 LED control output	Position 3 LED control input
9	I	Input for button 4 contact	Button 4 contact
10	-	Disconnected	Disconnected
11	-	Disconnected	Disconnected
12	O	Position 4 LED control output	Position 4 LED control input

Connector no. 4: Control unit with emergency stop and luminous disc




Pin	Type	P-Connect side	Control unit side
1	-	Disconnected	Disconnected
2	O	Control output luminous disc +24 Vdc	Control input luminous disc +24 V
3	O	Luminous disc power supply 0 Vdc	Power supply 0 V
4	-	Disconnected	Disconnected
5	O	Test output TO1	Emergency stop button test input
6	I	Safety input for emergency stop button NC contact	Emergency stop button NC safety contact
7	O	Test output TO2	Emergency stop button test input
8	I	Safety input for emergency stop button NC contact	Emergency stop button NC safety contact

Connector no. 5: AN series safety handles



Pin	Type	P-Connect side	AN side
1	I	0 Vdc power supply	Power supply 0 V
2	O	+24 Vdc power supply	Power supply +24 V
3	O	Control output LED 1	Control input green LED (G)
4	O	Control output LED 4	Button LED control input
5	O	+24 V output for button contact	Button NO voltage-free contact input
6	I	Input for button contact	Button NO voltage-free contact output
7	O	Control output LED 2	Control input blue LED (B)
8	O	Control output LED 3	Control input red LED (R)


Connector no. 6: Indicator light tower (reference wiring diagram)



Pin	Type	P-Connect side	Indicator light tower side
1	I	0 Vdc power supply	Power supply 0 V
2	O	+24 Vdc power supply	Power supply +24 V
3	O	Control output LED 1	Control input LED 1
4	O	Control output LED 4	Control input LED 4
5	O	Buzzer control output	Buzzer control input
6	I	Signalling input	Signalling output
7	O	Control output LED 2	Control input LED 2
8	O	Control output LED 3	Control input LED 3


BP A1•L2003

Connectors no. 1 & 2: NG - NS series safety switches



Pin	Type	P-Connect side	NG - NS side
1	O	Single-channel solenoid activation output	I4
2	O	Short circuit +24 VDC	IS1
3	O	Short circuit +24 VDC	IS2
4	I	Safety input IS1/IS3	OS1
5	I	Safety input IS2/IS4	OS2
6	O	+24 Vdc power supply	A1
7	O	Actuator programming / reset	I3
8	I	Actuator enabled signal input	O3
9	I	Locked guard signal input	O4
10	O	Test output TO1	Emergency stop button test input
11	I	Safety input for emergency stop button NC contact	Emergency stop button NC safety contact
12	-	Not connected	I5
13	O	Test output TO1	Emergency stop button test input
14	I	Safety input for emergency stop button NC contact	Emergency stop button NC safety contact
15	I	Input for position 2 contact	Position 2 contact
16	O	Position 2 LED control output	Position 2 LED control input
17	I	Input for position 1 contact	Position 1 contact
18	O	Position 1 LED control output	Position 1 LED control input
19	I	0 Vdc power supply	A2

Connectors no. 3 & 4: AN series safety handles




Pin	Type	P-Connect side	AN side
1	I	0 Vdc power supply	Power supply 0 V
2	O	+24 Vdc power supply	Power supply +24 V
3	O	Control output LED 1	Control input green LED (G)
4	O	Control output LED 4	Button LED control input
5	O	+24 V output for button contact	Button NO voltage-free contact input
6	I	Input for button contact	Button NO voltage-free contact output
7	O	Control output LED 2	Control input blue LED (B)
8	O	Control output LED 3	Control input red LED (R)




BP A1•L2004

Connector no. 1: Series NG/NS/NX/ST safety switches via VF CY




Pin	Type	P-Connect side	Switch side
1	O	+24 Vdc power supply	A1
2	I	Safety input IS1	OS1
3	O	0 Vdc power supply	A2
4	I	Safety input IS2	OS2
5	I	Safety output DO1	I3/IE1

Connector no. 2: Series NG/NS/NX/ST safety switches via VF CY




Pin	Type	P-Connect side	Switch side
1	O	+24 Vdc power supply	A1
2	I	Safety input IS3	OS1
3	O	0 Vdc power supply	A2
4	I	Safety input IS4	OS2
5	I	Safety output DO2	I3/IE1

Connectors no. 3, 4, 5 & 6 BN AC3Z... or BN AC4Z... series control device units



Pin	Type	P-Connect side	BN side
1	O	+24 Vdc power supply	Power supply +24 V
2	I	Position 1 LED control output	Position 1 LED control input
3	O	0 Vdc power supply	Power supply 0 V
4	I	Input for button 1 contact	Button 1 contact
5	I	Input for button 2 contact	Button 2 contact
6	O	Position 2 LED control output	Position 2 LED control input
7	I	Input for button 3 contact	Button 3 contact
8	O	Test output TO1 (1)	Emergency stop button test input
9	I	Safety input IS5 for NC contact of emergency stop button	Emergency stop button NC safety contact
10	O	Test output TO2 (1)	Emergency stop button test input
11	I	Safety input IS6 for NC contact of emergency stop button	Emergency stop button NC safety contact
12	O	Position 3 LED control output	Position 3 LED control input

Numbering of control devices



Legend:


- A1 = Supply input +24 Vdc
- A2 = Supply input 0 V
- IE1, IE2 = Solenoid activation inputs
- O3 = Signalling output, actuator inserted
- O4 = Signalling output, actuator inserted and locked
- ISx = Safety inputs
- OSx = Safety outputs
- I3 = Actuator programming input/reset
- I5 = EDM input (cannot be used on BP series)
- I = Device input
- O = Device output

Notes


[illegible]This image shows a full page of blank graph paper. The grid consists of small, equal-sized squares formed by thin black lines. There are 20 columns and 20 rows of squares, creating a total of 400 square units. The lines are evenly spaced and extend across the entire area of the page, leaving no margins or additional markings.



[illegible]A full page of blank graph paper with a uniform grid of small squares. The grid consists of 20 columns and 20 rows, creating a total of 400 small square units. The lines are thin and black, set against a white background. There are no margins or additional markings on the page.




General Catalogue
Detection



General Catalogue
HMI



General Catalogue
Safety
Devices



General Catalogue
- PLCs & Safety
Modules



General Catalogue
Lift



Website
www.pizzato.com



Pizzato Elettrica s.r.l. via Torino, 1 - 36063 Marostica (VI) Italy

Phone: +39 0424 470 930

E-mail: info@pizzato.com

Website: www.pizzato.com

Any information or application example, connection diagrams included, described in this document are to be intended as purely descriptive. The choice and application of the products in conformity with the standards, in order to avoid damage to persons or goods, is the user's responsibility. The drawings and data contained in this document are not binding and we reserve the right, in order to improve the quality of our products, to modify them at any time without prior notice. All rights to the contents of this publication are reserved in accordance with current legislation on the protection of intellectual property. The reproduction, publication, distribution and modification, total or partial, of all or part of the original material contained therein (including, but not limited to, texts, images, graphics), whether on paper or in electronic form, are expressly prohibited without written permission from Pizzato Elettrica Srl. All rights reserved. © 2025 Copyright Pizzato Elettrica

ZE FGL29A25-ENG

